

Azan with Iqamah Panel



Model: QP-15F


User Manual



**Systems
Integration**
Electronics & Communication Solutions

Head Office:

Office # 412, 4th Floor, Madina City Mall, Abdullah Haroon Road,
Saddar, Karachi, Pakistan.

Tel: +92(21)-35217256, 35654771-74 / Cell  : +92-3360837535

Panel have 5 menu selections to set different parameters:

- 1 - JAMAT SET 2 - TIME SET 3 - HIJRI SET
4 - VAR SET 5 - CITY SET

A rectangular LED display with a black background and green characters showing the text "JAMAT SET".

JAMAT SET (Iqamah Time Setting)

- Press (5) then press (MENU) until [JAMAT SET] starts blinking.
- Press (SET) to enter set mode, Fajr hours starts blinking.
- Use (+) / (-) for setting. Press (SET) and (+) / (-) to set minutes.
- Set all Jamat Times one by one then Exit.

Offset Option:

- We can set all Salah time by Offset method except Juma.
 - For example: To set Fajr offset, keep Fajr Hour 00 and Minutes as required offset time.
- Fajr Jamat time can be set to follow Fajr Azan time.
Fajr Jamat time will be changed as Azan time changed.
- We can fix Jamat time of Jummah.

A rectangular LED display with a black background and green characters showing the text "TIME SET".

TIME SET (Time and Date Setting)

- Press (5) then press (MENU) until [TIME SET] starts blinking.
- Press (SET) , second starts blinking. Press (+) for set 00.
- Use (SET) and (+) / (-) to set Time and Date Parameters one by one.

HIJRI SET

HIJRI SET (Hijri Date Adjustment)

- Press (5) then press (MENU) until [HIJRI SET] starts blinking.
- Press (SET) to enter set mode, Hijri date starts blinking.
- Use (+) / (-) to Increment or Decrement Hijri Date.

VAR SET

VAR SET (Set Different Variables)

- Press (5) then press (MENU) until [VAR SET] starts blinking.
- Press (SET) to enter set mode.

Set the following Variables one by one:

ENG

Set Language:

We can set English / English + Arabic / Arabic

الجمعة 0

Set Juma Enable/Disable:

Set Juma 0 to disable or set Juma 1 to enable Juma Jamat time.

✓ SPEAKER

Set Speaker Enable/Disable:

X SPEAKER

Set Check to ON speaker for Takbeer and Qad Qamatis Salah and Set Cross to OFF speaker.

✓ BEEP

Identify Prohibited Time through Beep sound:

Indication with Beep sound in Prohibited Time of Sunrise or Zawal.

✓ DST

Day Light Saving:

ON: 1 Hour added to current time and all Salah Times.
OFF: To disable DST.

CITY SET

CITY SET (Set The City)

- First find the required city code from the city code list.
- Press **5** then press **MENU** until [CITY SET] starts blinking.
- Press **SET** to enter set mode.
- Press **+**/**-** for select the code then press **SET** to save code.

